NATIONAL VENDORS FACTORY INSPECTION RECORD

ACCEPTED	■ REJECTED	CUSTOMER ADDRESS MODEL SERIAL NO. CONTROL NO. INSPECTION DATE: CHANGER NO. & MODEL VALIDATOR NO. & MODEL CARD READER NO. & MODEL TEST AND INSPECTION TO BE IN VISUAL INSPECTION 01. Tube routing, electrical harm 02. Correct display and menu p 03. Machine built as per work tie 04. General visual inspection fo 05. Exterior cabinet appearance 06. Properly painted and plated 07. Inventory of miscellaneous o 08. Jumper plugs as required. 09. Serial and control numbers	ess, and label placement anels. cket including all options or door to cabinet fits, scree. parts. components.	and accessories. atches, cleanliness, etc.	_		
		ELECTRICAL INSPECTION O1. Proper insulation on electrical termination. O2. All electrical connections secure, wire harness routing and dressing to code. O3. Ground securely installed and tested. O4. High voltage breakdown test. O5. Check all metal parts for burrs - cabinet, shelves, door, cup station, etc. O6. Safety covers and guards in place and secure.					
NOTE	E: A	 13. Test exact change, sold out 14. Display and work lights. 15. Coffee chute and module ch 16. Water tank temperature: 20 17. Water throws - 8¼ oz. cup of 	d door controller - function. oring setting and delivery rand hose routing. Fit to door and adjust many switch is activated, meromatic (optional) vend donechanism and coins. Of and credit display functionate alignment - canister 12° / 205° F. unless otherwise specification product 180 ml; chocolation inched).	nug switch (optional). chandiser will not vend. or. perate coin return mechanism. ons. alignment. ed: Fresh brew coffee 220 ml; freeze dry ofte 170 ml	coffee &		
the item was rejected, repaired, reinspected, and found to be acceptable.			Inspector's stamp	Initials	Date		

Work performed by:

Date:

L	NOTE:	A mark in this column indicates completion of work.	Final Pack Part No. 3630009 Sheet 3 of 3
	01.	Install plastic miscellaneous components bag containing set-up instructions, to door.	
	02.	Install electrical code tag on power cord.	
	03.	Install packing boxes.	
	04.	Install and tape waste containers with appropriate contents.	
	05.	Install packing to cup dispenser and tape.	
	06.	Tape coin box, vend door, and changer mounting brackets.	
	07.	Tape overflow switch.	
	08.	Add water filter cartridge, if specified.	
	09.	Make final visual check.	
	10.	Program lock to proper key and place key in coin cup.	
	11.	Tape electrical power cord to rear of cabinet.	
	12.	Tape down syrup tank lids (363, 365 only).	
	13.	Install syrup tanks, syrup tank tubes and lids (363, 365 only).	
	14.	Install syrup B.I.B. fittings per order (364, 366 only).	
	15.	Install rear screens.	
Date:		Work performed by:	

Γ

	■ NOTE: A mark in this column indicates completion of work.		Boxing
♣			
	01.	Remove factory inspection record.	
	02.	Install shipping bag over machine.	
	03.	Install tube over cabinet.	
	04.	Install top pad on cabinet.	
	05.	Install top carton on cabinet.	
	06.	Apply stencil and shipping ticket on packing tube.	
	07.	Scratch key number off ticket.	
	08.	Check invoice number on work sticker against pink copy.	
	09.	Staple top and bottom cartons.	
	10.	Affix trucking information label.	
Date:		Work performed by:	